




Optional steel case showed. Order number **CA-002**

This 10W single-ended toroidal output transformer is specifically designed for high-end Hi-Fi audio amplifiers. It features a precision-engineered toroidal core with carefully calculated air gaps to support proper DC biasing and enhance audio performance. The design minimizes distortion and improves frequency response, delivering clean, detailed sound reproduction. Compatible with most commonly used output tubes, this transformer offers an excellent solution for audiophiles seeking superior sound quality in single-ended amplifier designs.

SPECIFICATION:

Output power	10 Watt
Turn Ratio	30:1
Primary impedance	3K, 5K, 7.0K ohm
Primary inductance	3.2, 5.3, 7.3 Henry
Primary DC resistance	108, 136, 158 ohm
Output impedance	4 & 8 ohm
Output DC resistance	0.35 & 0.56 ohm
Max bias current	100mA
Frequency response	20Hz - 50KHz
Size	Ø = 2.7" H = 1.75"
Weight	1 LB
Suggest Tubes	6L6, 6V6, EL34, EL84



The 3K tap can be considered as ultra linear tap

Frequency Response with 8 ohm Load

